

marantz®



RX8001 – WiFi Extender

As an accessory for the RC9001 this out-of-the-box stand-alone Wi-Fi Extender with zero installation and configuration effort will enhance your multi-room experience to new dimensions. The RX8001 is able to operate in a wireless or a wired network. By default, the RC9001 is using infrared (IR) to operate the programmed AV components. This means that you have to point the remote towards the device you're operating. Normally, IR signals have an operating distance of maximum 10 meter. You can choose to operate devices using radio frequency Wi-Fi signals instead of IR signals. Depending on the circumstances, Wi-Fi signals have a much larger operating distance in house. The Wi-Fi signals sent out by the RC9001 are picked up by the external Wi-Fi receiver RX8001. The receiver converts the Wi-Fi signal to an electrical signal which will send the converted IR signals to the appropriate component.

because music matters

marantz®



FEATURES	RX8001
System Control via CAT5 / Wireless	o/o (RC9001)
Customization via Webserver	o
Network mode	DHCP, Fixed IP
Addressable IR Emitter outputs	4
Adjustable IR output level	o
IR code range	25kHz - 1Mhz
RS232 serial interface	-
Relay outputs	-
DC Output	-
Power sense input	-
Status indication	2 LED
ACCESSORIES	
AC adaptor	5V DC / 2A
Crossover configuration cable	o
IR Emitter	2x Dual IR
Mini-jack IR cable	2
Rackmount kit	-
GENERAL	
Colour: Black	o
Dimensions (W x H x L) in mm	157 x 33 x 100
Weight in kg	0.18

Design and specifications are subject to change by Marantz without notice.

www.marantz.eu