



**marantz®**

## Product information

### SR5023 STEREO RECEIVER



This latest 2x 80W stereo receiver, in the M1 Reference Style design, is built to the highest standards and expertly finished. The slim aluminium front expresses perfect balance, while the dimensions are the same as those for the CD5004 and SA7003, giving you the option of creating an extraordinary system from just two components. Close attention to detail and a no-compromise construction ensures faithfully captured excitement and emotional playback of your music. This RDS stereo receiver comes with FM/AM reception, 50 random presets and a powerful amplifier at its heart. For vinyl addicts there's also a high-quality phono MM pre-amplifier. Subwoofer output and a pairs of screw type speaker terminals make it a true centrepiece of your home stereo system.

#### Main Features

- 2x 80 Watts RMS 8 ohm
- RDS FM/AM Tuner
- Full dot matrix display
- 50 presets
- Source direct
- 6 analogue inputs including Phono MM
- Subwoofer Output
- System Remote Control

#### EAN

<b>EU</b>	SR5023/N1B	4951035037560
	SR5023/N1SG	4951035037577
<b>UK</b>	SR5023/T1B	4951035037584
	SR5023/T1SG	4951035037591

# because music matters



marantz®

## SR5023 STEREO RECEIVER



FEATURES	SR5023
Current Feedback Topology	-
Linear Drive Power Supply	0
Power Transformer: Toroidal / EI	- / 0
HDAM version	-
Symmetric PCB Layout	0
Balance / Bass / Treble / Loudness	- / 0 / 0 / -
Source Direct	0
Speaker A / B	-
Phono EQ	0
Standby Mode	0
Full Dot Matrix Display	0
Display Off	0
Display Dimmer	0
TUNER FEATURES	
Broadcast bands: FM / MW / LW	0 / 0 / -
Presets	50 (FM / AM)
Auto Tuning	0
RDS: PTY / PS / RT	0 / 0 / 0
Station Naming	0
Sleep / Timer	0 / -

INPUTS/OUTPUTS	
Audio Inputs	6
Phono Input: MM / MC	0 / -
Audio Outputs	1
Pre-Out / Main-in	- / -
Subwoofer Out	0
FM Antenna	0
AM Antenna	0
Marantz D-bus In / Out	0 / 0
Gold Plated cinch	-
Speaker Terminal: Screw / Marantz / WBT	0 / - / -
AC Outlets (Not for UK Model)	0
Headphone Out	0
iPod input (direct / docking station)	- / 0
SPECIFICATIONS	
Power Output (8 / 6 ohm)	80 / 100W
Frequency Response	10Hz-50kHz (+0,-1dB)
Total Harmonic Distortion	0.03%
Damping Factor	100
Input Sensitivity: MM / MC	2.5mV / 47kohm / -
Signal to Noise Ratio MM / MC	83dB / -
Input Sensitivity: High Level	200mV / 20kohm
Signal to Noise Ratio High Level	90dB

GENERAL	
Available colors: Gold / Silver / Black / Silver-Gold	- / - / 0 / 0
Metal Front Panel	0
Remote Control	RC002SR
Power Consumption in W	150
Standby Consumption in W	0.4
Detachable Power Cable	0
Maximum Dimensions (W x D x H) in mm	440 x 367 x 105
Weight in kg	7.8

# because music matters

www.marantz.eu

Design and specifications are subject to change by Marantz without notice.