

marantz®



ST6003 – Stereo Tuner

The ST6003 is an FM/MW Stereo analogue tuner with access to all major frequencies and has a high-sensitivity front end to ensure drift-free reception. The RDS tuner lets you tune by frequency or program type, while the new full dot matrix display clearly indicates the frequencies and radio data such as station name or radio text. It comes with 50 station presets and a sleep timer function. And, via the Marantz D-Bus you can remote control the ST6003 with any Marantz amplifier remote or optional RC101. In total, the ST6003 combines high-quality audio components for the best sound with functionality and ease of use.



because music matters

marantz®



FEATURES		ST6003	SPECIFICATIONS	
Broadcast bands: DAB / FM / MW / LW		-/o/o/-	TUNER SECTION FM	-
Dual Gate MOS-FET		-	Frequency Range	87.5 - 108 MHz
IF Bandwidth Selector		-	Signal to Noise Ratio (Mono/Stereo)	75 / 70 dB
Customised Components		o	Total Harmonic Distortion (Mono/Stereo)	0.2 / 0.3 %
Presets		50(FM/AM)	Frequency response	50Hz - 15kHz (+0.5dB/-3dB)
Auto Tuning		o	Channel Selectivity (FM)	60 dB
RDS: PTY/PS/RT		o/o/o	Usable Sensitivity	IHF 1.8 µV / 16.4 dBf
Sleep / Timer		o/-	Stereo Separation	1 kHz, 45 dB (Stereo)
Birdy Whistle Elimination Circuitry		-	TUNER SECTION AM	-
Full dot matrix display		o	Frequency Range: MW / LW	531-1602 kHz / -
Gyro Touch Tuning		-	Signal to Noise Ratio: MW / LW	50 dB / -
Display dimmer (via external RC)		o	GENERAL	
Triple IR-code		o	Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/o
IN/OUTPUTS			Metal Front Panel	o
Analogue Out		1	Remote Control	via D-Bus
D-Bus		o	Power Consumption in W	9
FM Antenna		1	Standby Consumption in W	0.4
AM Antenna		1	Detachable Power Cable	o
			Maximum Dimensions (W x D x H) in mm	440x341x104.5
			Weight in kg	4.1

Design and specifications are subject to change by Marantz without notice.

www.marantz.eu