

SA8001

SUPER AUDIO CD PLAYER



Marantz proudly presents a triumphant achievement: the remarkable SA8001 Super Audio CD player. By incorporating our vast knowledge with the development of the SA-11S1 and SA-15S1 SACD players, Marantz is now able to deliver the depth, dynamics and sonic accuracy at a remarkable new price. Improving on a legendary platform (the SA8260 - five years on Stereophile Magazine's Recommended Components list), the SA8001 will find its way onto every budget minded music lover's wish list.

- Plays Stereo SACD, CD, CD, CD-R/RW
- Current Feedback Circuit with Marantz Original HDAM®
- Cirrus Logic CS4397 DAC with Digital Filter
- Exclusively Designed Original Mechanism for Audio Playback
- Zero Impedance Copper Ground Plate for Analog Terminals
- Double Layered Bottom Chassis
- Audiophile Grade Power Supply Unit with Toroidal Transformer
- Audiophile Grade Selected Components and Terminals
- Quick Replay mode
- High Quality Headphone Circuit
- Super Audio CD Text
- D-BUS (RC-5 In/Out) Remote Connection
- Detachable Power Cord
- Device Remote

FEATURES

| | |
|------------------------------|--------------------------|
| Disc Capacity | 1 |
| Multi-ch Capability | - |
| Playback Formats | SACD-Stereo, CD, CD-R/RW |
| HDAM | • |
| Power Transformer | Toroidal |
| Zero-Impedance Plate | - |
| Double Layered Bottom Plates | • |
| Audio DAC | 192kHz/24-Bit |
| Display On/Off | • |
| Selectable Filters | - |
| SACD/CD Text | • (SACD) |

IN/OUTPUTS

| | |
|----------------------------|----------------|
| AUDIO | |
| Analog L&R Out | 1 (Unbalanced) |
| Analog 5.1ch Out | - |
| Digital Opt. Out | 1 |
| Digital Coax. Out | 1 |
| Headphone Out | • |
| OTHER | |
| D-Bus Remote (RC-5) In/out | 1/1 |

GENERAL

| | |
|-------------------------------|--|
| Color | Black |
| Faceplate | Aluminum |
| Remote | Device Remote RC8001SA |
| Power Requirement | AC 120V 60Hz |
| Power Consumption | 20W |
| Dimensions W x H x D (Inches) | 17 ⁵ / ₁₆ " x 5" x 13 ³ / ₁₆ " |
| Weight (lbs.) | 17.6 |



SPECIFICATIONS

| | |
|----------------------------|------------------|
| SACD | |
| Format | 1-Bit DSD |
| Sampling Frequency | 2.8224MHz |
| Dynamic Range | 112 dB |
| Frequency Response (-3 dB) | 2Hz - 50kHz |
| THD | 0.001% |
| CD AUDIO | |
| Format | 16-Bit Liner PCM |
| Sampling Frequency | 44.1kHz |
| Dynamic Range | 100 dB |
| Frequency Response | 2Hz - 20kHz |
| THD | 0.002% |



marantz[®]
LIFE AMPLIFIED™

*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors in this spec sheet which may result in consequential errors being made by retail dealers, designers, custom installers, cabinet makers or end users, etc based upon information contained within this document.