

marantz®

SA8260 Multi-Channel Super Audio CD Player

Marantz proudly presents a triumphant achievement: the remarkable SA8260 Super Audio CD player. By incorporating our vast knowledge with the development of the SA-1, SA-12S1, SA-14, and SA-14v.2 SACD players, Marantz is now able to deliver the depth, dynamics and sonic accuracy at a remarkable new price. Reflecting the success of the highly acclaimed CD-63SE, the SA8260 is destined to be the next legend.



**RECOMMENDED "CLASS A" BY
STEREOPHILE MAGAZINE
(APRIL 2004)**



FEATURES

Disc Capacity	1
Multi-ch Capability	•
Playback Formats	SACD-Multi/Stereo, CD, CD-R/RW
HDAM	•
Power Transformer	EI
Zero-Impedance Plate	•
Double Layered Bottom Plates	•
Audio DAC	192kHz/24-Bit
Display On/Off	•
Selectable Filters	•
SACD/CD Text	•

IN/OUTPUTS

AUDIO	
Analog L&R Out	1
Analog 5.1ch Out	•
Digital Opt. Out	1
Digital Coax. Out	1
Headphone Out	•
OTHER	
D-Bus Remote (RC-5) In/out	1/1

SPECIFICATIONS

SACD	
Format	1-Bit DSD
Sampling Frequency	2.8224MHz
Dynamic Range	113 dB
Frequency Response (-3 dB)	2Hz - 50kHz
THD	0.0015%
CD Audio	
Format	16-Bit Liner PCM
Sampling Frequency	44.1kHz
Dynamic Range	100 dB
Frequency Response	2Hz - 20kHz
THD	0.0020%

GENERAL

Color	Black
Faceplate	Aluminum
Remote	RC8260SA
Power Requirement	AC 120V 60Hz
Power Consumption	28W
Dimensions W x H x D (Inches)	17 ¹ / ₁₆ " x 4 ³ / ₁₆ " x 12 ¹ / ₁₆ "
Weight (lbs.)	17

- Plays Back: SACD-Stereo/Multi-Channel, CD, CD-R/RW Discs
- Marantz Original High Accuracy SACD Drive Module
- CS4397 DACs by Cirrus Logic®
- Current Feed Back HDAM Circuits for All Analog Audio Outputs
- Audiophile Grade Capacitors
- Double Layered Chassis Construction
- "Zero Impedance" Copper Ground Plate for Analog Output Terminals
- Gold Plated Terminals
- D-BUS (RC-5 In/Out) Remote Connection



*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors within this document.