

marantz®



CC4001 – CD Changer

With a five-disc carousel, fully programmable playback mode as well as random, repeat and scan modes, the CC4001 CD Changer provides endless combinations of non-stop music. Its multi-read drive plays not only CDs but also CD-R/RWs with MP3 encoded music. The Digital Servo Drive ensures accurate reading and fast track access. Both coaxial digital and optical outputs are provided to make digital recordings. The unit incorporates a headphone output with adjustable volume, and the dedicated remote controller provides direct disc access. The metal chassis and solid metal front panel provide a rigid base for high-quality performance. The Marantz D-Bus system and a built-in RS232C port with discrete coding provide an open architecture for enhanced system control.



because music matters

marantz®



FEATURES	CC4001	SPECIFICATIONS	
Disc Capacity	5	Mechanism	KSS-213CCM
CD Compatibility: CD / CD-R/RW / SA-CD / WMA / MP3	o/o/-/-/o	Decoder	CXD3068Q
SA-CD compatibility: Multi channel / stereo	-/-	D/A Conversion	Multi-bit, Delta-Sigma
CD-Text / SA-CD Text / ID3 Tag/ WMA Meta Tag	-/-/-/-	DAC IC	CS4392
High Grade Audio Components	o	Digital Filter	CS4392
Customized Components	-	Noise Shaper	CS4392
Symmetric circuit layout	-	Low Pass Filter stage	NJM2068
Power Transformer: Toroidal / EI	-/o	Output Buffer	-
HDAM version	-	Headphone amp	NJM4556
Shottky diodes	-		
Zero Impedance Matching joint (copper)	-		
Separated rectifier circuit for analogue and digital circuitry	-	CDDA AUDIO	
Digital out off / Audio EX Mode	- / -	Frequency Response	20Hz- 20 KHz
Display: Dimmer / Off	o/-	Dynamic Range	100dB
Headphone: Standard / Buffer / Current feedback	o/-/-	Signal to Noise Ratio	100dB
Copper plated chassis	-	Total Harmonic Distortion	0.002
Extra metal plate for chassis strengthening	-	Channel Separation	110dB
		GENERAL	
PLAYBACK		Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/-
Program Play	32	Metal Front Panel	o
Auto Music Scan (AMS)	o	Remote Control	RC4001CC
Repeat: track/program/A-B	o/o/o/-	Power Consumption in W	19
Random Play	o	Standby Consumption in W	0.6
Peak Search	-	Detachable Power Cable	o
Edit Recording	-	Maximum Dimensions (W x D x H) in mm	440x404x114
Pitch Control	-	Weight in kg	6.9
Start Sound Mode for SA-CD	-		
Quick Replay	-		
INPUTS/OUTPUTS			
Analogue Out (Cinch)	2ch		
Digital Optical Out	1		
Digital Coaxial Out	1		
Gold plated Cinch	o		
USB	-		
D-Bus	o		
RS-232C	o		
Headphone Out	o		
Headphone Volume Control	o		



Design and specifications are subject to change by Marantz without notice.