

# marantz®

## SR6011

### 9.2 CHANNEL NETWORK AV RECEIVER WITH BLUETOOTH AND WI-FI



Immerse yourself in stunning 3D surround sound with the SR6011 AV receiver featuring Dolby Atmos and DTS:X. The SR6011 is equipped with 9 channel amplification, which means you can setup a 7.1.2 or 5.1.4 3D experience without the need of external amplifier. If you like to take advantage of the 11.2ch processing just add an 2ch power amplifier and enjoy Dolby Atmos or DTS:X up to a 7.1.4 configuration. If not in use for 3D audio the integrated amplifiers can get assigned to drive another pair of speakers in a second audio zone running a different source than the main room. Prepared for the future, the SR6011 features an advanced video section that's fully compatible with the latest HDMI 2.0a and HDCP 2.2 specifications on all 8 HDMI inputs.

#### Highlights

9.2 channel AV Receiver with 185W per channel  
 Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth  
 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020  
 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 2 HDMI outputs  
 Analogue to HDMI conversion and full SD/HD to 4K Upscaling  
 Dolby Atmos (up to 7.1.4) and DTS:X (via firmware update)  
 AirPlay, Bluetooth, Internet Radio, Spotify Connect, Network Audio Streaming  
 DSD (2.8/5.6MHz), FLAC, ALAC, AIFF and WAV support  
 Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ  
 Colour-coded speaker terminals, Setup Assistant, Marantz 2016 AVR Remote App  
 Intelligent ECO mode with off/on/auto setting  
 Advanced Multi-Room options; 11.2ch pre-out with 11.2ch processing;  
 RS232 Control; Crestron Connected

#### Your Benefits

Enough power to fill big rooms with renowned Marantz sound  
 Improved network stability especially in WiFi-crowded homes  
 Latest HDMI standard for future-proof compatibility  
 Extended connectivity: ready to feed a TV and projector in parallel  
 HD video quality from existing DVDs or analogue sources  
 Immersive 3D sound with effects from overhead  
 Access to almost unlimited online music sources  
 High Resolution audio streaming, even gapless  
 Delivering the ultimate equalization for your individual room  
 Hassle-free installation, setup and operation  
 Energy-conscious without compromising on performance  
 Audio and video in multiple rooms; ready for 3rd Party Home Automation systems

www.marantz.eu



# because music matters

## SR6011

### 9.2 CHANNEL NETWORK AV RECEIVER WITH BLUETOOTH AND WI-FI



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR6011
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAx2	•
<b>NETWORK / SOURCES</b>	
Network Audio Streaming	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (vTuner)	•
Spotify Connect *	•
Compatible with Remote APP	Android/iOS/Kindle
Ethernet / Wi-Fi	• / • (dual antenna / 2.4/5 GHz)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
FM / AM Tuner	• / •
Bluetooth	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Video processing and -scaling	1080p, 4K 60/50Hz
<b>INPUTS/OUTPUTS</b>	
<b>VIDEO</b>	
Composite In / Out	3+1 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 2

<b>AUDIO</b>	
Analogue In / Out	5+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (11.2 with 11.2 processing)
Zone audio preout	•
Subwoofer Out	2
7.1 Multichannel input	•
<b>SPECIFICATIONS</b>	
Number of poweramps	9
Power Output per channel	
6 ohm, 1 kHz, 1%, 1ch Drive	185 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	150 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	110 W
Audio Signal to Noise Ratio	102 dB
<b>GENERAL</b>	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC025SR
Power Consumption in W	680
Power Consumption No-Sound (ECO ...on/off) in W	50 / 80
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	440 x 398 x 161
Weight in kg	12.7
<b>EAN</b>	
<b>EU</b>	SR6011/N1B 4951035058794 Black
	SR6011/N1SG 4951035058800 Silvergold
<b>UK</b>	SR6011/T1B 4951035060148 Black
	SR6011/T1SG 4951035060155 Silvergold

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* This feature is not available in all countries.

\* All specs can be subject to change.