

# marantz®



## SR7012 9.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY

Marantz has long set the standard for AV receivers combining home theater prowess with superb music ability. The SR7012 takes that capability to unprecedented levels, combining full 4K compatibility and unparalleled 3D surround sound decoding with precision audio engineering and tuning for an immersive movie experience.

### Highlights

### Your Benefits

9.2 channel AV Receiver with 200W per channel	Enough power to fill big rooms with renowned Marantz sound
Dolby Atmos and DTS:X (up to 7.1.4 with external 2 channel amplifier), Auro-3D	Immersive 3D sound with effects from overhead
Marantz sound tuning with all-new components, including current feedback HDAM preamp	Designed for movie and music purity for all-round entertainment capability
High performance 192kHz/32bit D/A converters for all channels	Highest resolution for music and movie sound
Audyssey MultEQ XT32, LFC, Sub EQ HT, Dynamic Volume and Dynamic EQ	Delivers the ultimate equalization for your individual room
Built-in Wi-Fi with 2.4GHz/5GHz dual band support	Improved network stability, especially in Wi-Fi-crowded environments
HEOS Music Streaming Technology with HEOS app	Comfortable control options, nearly unlimited music sources and multi-room experience with additional HEOS products
AirPlay, Bluetooth, Internet Radio, Spotify Connect, TIDAL, Deezer	Access to nearly unlimited online music sources
Network Streaming: DSD (2.8/5.6MHz), FLAC, ALAC and WAV support	High resolution audio streaming for HiFi enthusiasts
4K/60 Hz, 4:4:4, HDR and BT.2020, Dolby Vision compatible, HLG	Latest HDMI standard for future-proof compatibility
8 HDMI inputs (including 1 front) with full HDCP 2.2 support; 3 HDMI outputs (zone)	Plenty of inputs for your digital devices play different video in different rooms
eARC (Enhanced Audio Return Channel) via future firmware update	Allows 3D audio transmission from TV via HDMI audio return channel
Colour-coded speaker terminals, Setup Assistant, Marantz AVR Remote app	Hassle-free installation, setup and operation
Advanced multi-room options; 11.2ch pre-out; RS232 control; Crestron Connected, IP-control	Audio and video in multiple rooms; ready for third-party home automation systems



# because music matters

## SR7012

### 9.2 CHANNEL NETWORK AV RECEIVER WITH HEOS MUSIC STREAMING TECHNOLOGY



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR7012
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / •
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Auro-3D / Auroomatic	• / •
Multichannel Stereo	•
Compressed audio enhancer: MDAx2	•
Audyssey	MultEQ XT32 with LFC/Sub EQ HT
Audyssey Dynamic EQ / Dynamic Volume	• / •
Audyssey MultEQ editor app support	•
<b>NETWORK / SOURCES</b>	
Network audio streaming	•
HEOS multi-room integrated	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 192/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (Tuneln)	•
Spotify Connect, Deezer, TIDAL, Napster, Soundcloud *	• / • / • / • / •
Compatible with Remote APP for smart phones	Android/iOS
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB audio	•
FM / AM tuner	• / •
Bluetooth	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
eARC (Enhanced Audio Return Channel)	• (via Firmware Update)
Dolby Vision compatible / Hybrid Log Gamma (HLG)	• / •
HDMI pass-through on stand-by	•
3D video pass-through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Videoprocessing and -scaling	1080p, 4K 60/50Hz

\* This feature is not available in all countries.

Sound United  
1 Viper Way  
Vista, CA 92081  
United States

<b>INPUTS/OUTPUTS</b>	
<b>VIDEO</b>	
Composite in / out	3+1 / 2
Component in / out	3 / 1
HDMI in / out	7+1 / 3 (2 main + 1 zone)
<b>AUDIO</b>	
Analog in / out	5+1 / 0
Digital optical in	2
Digital coaxial in	2
Multichannel pre-out	• (11.2 with 11.2 processing)
Zone audio pre-out	2
Subwoofer out	2
7.1 Multichannel input	•
<b>SPECIFICATIONS</b>	
Number of poweramps	9
Power output per channel	
8 ohm, 20 Hz - 20kHz, 0.08%, 2-channel drive	110 W
8 ohm, 20 Hz - 20kHz, 0.05%, 2-channel drive	125 W
6 ohm, 1kHz, 0.7%, 2-channel drive	165 W
6 ohm, 1kHz, 10%, 1-channel drive	235 W
Audio signal to noise ratio	102 dB
<b>GENERAL</b>	
Available colors	Black
System remote control	RC036SR
Power consumption in W	710
Power consumption no-sound (ECO ...on/off) in W	65 / 110
Standby consumption in W	0.2 (with CEC 0.5)
Maximum dimensions (W x D x H)	17.3 x 16.2 x 7.3 in
Weight	31.1 lbs
<b>UPC</b>	
NA SR7012/U1B	699927151157 Black

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.